PHS-06A PHOTO ELECTRIC CONTROLLER

PHS-06A-1
PHOTO ELECTRIC
CONTROLLER

PHS-06A-2
SOCKET



REMARK:

- **PHS-06A (PHOTO ELECTRIC CONTROLLER WITH SOCKET)**
- **PHS-06A-1 (PHOTO ELECTRIC CONTROLLER ONLY)**
- **PHS-06A-2 (SOCKET ONLY)**

Introduction:

PHS-06A is designed for automatic light control. It can be used to turn on streetlights at night and turn off at dawn.

Safety Precaution:

Any improper use of this product can cause short circuit, which can damage product itself or even cause fire.
Please read instruction carefully and make sure:
1.Wiring and mounting position are correct according to instruction.
2.Auto lighter must work within rated current and voltage.

Technical Data:

1) Rated voltage: 105-305VAC
2) Rated frequency 50-60Hz
3) Rated current : 10A
4) Max Load: 1000W, 1800VA
5) Working Environment: 32-122˚F(0˚C～50˚C)
6) Acting time:
   Turn on in 30 seconds when light level ≤ 10Lux
   Turn off in 2 minutes when light level ≥ 70Lux
7) Specification:
   Weight: 220g
   Size: 110mm x 90mm x 85mm

Installation:

1) Install with sensor face up to the sky as show in picture
2) Window on the sensor should not face potential light sources
3) Connect wires to circuit as following:
   Load: Red wire
   Common: White wire
   Source: Black wire
4) Mount light sensor to supporting structure with metal support.

